



# L131

**Application:** Exterior/interior surface mount downlight.

**Source:** 3 x 2.5W, 700mA LEDs.

**Driver:** Integral 120V primary, 9W 700mA non-dimmable driver or remote 12V AC magnetic transformer (not included).

**Power Consumption:** 9W

**Power Supply: DC-** Power by integral 120V primary, 9W 700mA non-dimmable driver. Dimmable with TLDAV60W12 and TLC010i (dimming controller), 0-10V dimming (not included). Consult factory. **AC-** 12V AC magnetic transformer (not included). Consult factory for dimming option.

**Weight:** 0.88lbs (0.39kg).


**Material:** Anodized aluminum. RoHS compliant.

**Mounting:** Mounts to standard octagonal box (not included).

**Approval:** Damp and dry locations. Approved to US and Canadian standards by CSA.




**Note:** Can be used as emergency backup lighting in conjunction with Bodine emergency LED driver. Consult MP Lighting factory.



**L131**  
30°  
3000K Std  
266 lm


**Polar Candela Distribution**



**Illuminance at a Distance**

	Center Beam FC	Beam Width	
3.0'	102.3	1.6'	1.6'
6.0'	25.6	3.2'	3.2'
9.0'	11.4	4.8'	4.8'
12.0'	6.4	6.4'	6.4'
15.0'	4.1	8.0'	8.0'
18.0'	2.8	9.6'	9.6'

■ 0° Spread: 31.3°    ■ 90° Spread: 31.3°



**Note:** Various operating factors may cause differences between lab and field results. As specifications may change without notice, please refer to the LED Lamp Index located in the "Downloads" section of each product webpage for the most current information.

CODE	WATTAGE	COLOR	BEAM	INPUT VOLTAGE	FINISH
L131	7				

7 = 3 x 2.5W

W27S = 2700K std CRI  
W30S = 3000K std CRI

30 = 30° beam  
60 = 60° beam

A = 12V AC  
D = DC

MA = matte clear anodized  
BA = black anodized

**Note:** Standard CRI has a value of 75-82.



t 1.877.708.1184 f 604.708.1185 www.mplighting.com  
16 West 4th Avenue, Vancouver BC V5Y 1G3, Canada