



L130

Application: Interior surface mount downlight.

Source: 3 x 2.5W, 700mA LEDs.

Driver: Integral 120V primary, 9W 700mA non-dimmable driver or remote 12V AC magnetic transformer (not included).

Power Consumption: 9W

Power Supply: DC- Power by integral 120V primary, 9W 700mA non-dimmable driver. Dimmable with TLDAV60W12 and TLC010i (dimming controller), 0-10V dimming (not included). Consult factory. **AC-** 12V AC magnetic transformer (not included). Consult factory for dimming option.

Weight: 0.84lbs (0.38kg).


Material: Anodized aluminum. RoHS compliant.

Mounting: Mounts to standard octagonal box (not included).

Approval: Dry locations. Approved to US and Canadian standards by CSA.




Note: Can be used as emergency backup lighting in conjunction with Bodine emergency LED driver. Consult MP Lighting factory.



L130
30°
3000K Std
266 lm


Polar Candela Distribution



Illuminance at a Distance

	Center Beam FC	Beam Width	
3.0'	102.3	1.6'	1.6'
6.0'	25.6	3.2'	3.2'
9.0'	11.4	4.8'	4.8'
12.0'	6.4	6.4'	6.4'
15.0'	4.1	8.0'	8.0'
18.0'	2.8	9.6'	9.6'

■ 0° Spread: 31.3° ■ 90° Spread: 31.3°



Note: Various operating factors may cause differences between lab and field results. As specifications may change without notice, please refer to the LED Lamp Index located in the "Downloads" section of each product webpage for the most current information.

CODE	WATTAGE	COLOR	BEAM	INPUT VOLTAGE	FINISH
L130	7				

7 = 3 x 2.5W

W27S = 2700K std CRI
W30S = 3000K std CRI

30 = 30° beam
60 = 60° beam

A = 12V AC
D = DC

MA = matte clear anodized
BA = black anodized

Note: Standard CRI has a value of 75-82.



t 1.877.708.1184 f 604.708.1185 www.mplighting.com
16 West 4th Avenue, Vancouver BC V5Y 1G3, Canada